

F U S E

lighting



ACACIA CHANDELIER
5023

CLASSIC BRONZE PODS WITH GOLD GILDED INTERIOR AND DARK ANTIQUE BRASS FRAME

© 2000-2020 FUSE LIGHTING.
ALL RIGHTS RESERVED.

ACACIA CHANDELIER

5023

HEIGHT: 3 1/2" (8.9 CM)

DIAMETER: APPROX. 34" (86.4 CM)

CABLES: 56 1/2" (143.5 CM)

OAH: 60" (152.4 CM)
(CAN BE SHORTENED ON SITE)

CEILING CANOPIES: FOUR 2" (5.1)
DIA. AND ONE 5" (12.7) DIA. CAN-
OPIES..

WEIGHT: APPROX. 90 LBS.

WIRING: LED TAPE 2700, 90CRI,
26.5 WATTS

METAL FINISHES

BRUSHED BRASS
LIGHT ANTIQUE BRASS
DARK ANTIQUE BRASS
MATTE BRASS
POLISHED NICKEL
SATIN NICKEL
OIL RUBBED BRONZE
PATINATED STEEL

POD OPTIONS

CLASSIC BRONZE
SATIN NICKEL
INQUIRE FOR CUSTOM POD FINISHES

DUTCH GILDING

GOLD
WHITE GOLD
PLATINUM

CANOPIES

PRIMER WHITE (PAINTABLE)

LED (LOW VOLTAGE)

2700K
90CRI

REMOTE 50WATT LOW-VOLT-
AGE TRANSFORMER IS REQUIRED
(SUPPLIED BY FUSE).

LOW VOLTAGE TRANSFORMER
APPROXIMATE SIZE IS (6.5 X 2.2 X 1.7)

VOLTAGE: 120 VOLTS - WALL TO
TRANSFORMER

VOLTAGE: 24 VDC - TRANSFORMER TO
LED TAPE

WIRING: LED TAPE

LED WATTAGE: 4.5 PER FOOT

*LED TAPE UL LISTED

*TRANSFORMER ETL LISTED



INSTALLATION

FOUR 2" CANOPIES MOUNT DIRECTLY
TO CEILING WITH TOGGLE BOLTS.


A SINGLE 5" CANOPY MOUNTS DI-
RECTLY TO JUNCTION BOX.

WIRE RUNS ALONG ONE OF THE FOUR
CABLES INTO THE 5" CANOPY AND
INTO THE CEILING CONNECTING TO
THE LOW VOLTAGE TRANSFORMER
(TO BE PLACED IN AN ACCESSIBLE
REMOTE LOCATION SUCH AS A CEILING
RECESS, ATTIC, CLOSET, CABINET OR
BASEMENT).

INSTALLATION TO BE DONE BY PRO-
FESSIONAL ELECTRICAL CONTRACTOR
ONLY.



SCONCE
1023



PENDANT
4023





TABLE LAMP
6023



BOOKSHELF LAMP
6023 SL

fuselighting.com

© COPYRIGHT FUSE LIGHTING.
ALL RIGHTS RESERVED.