

F U S E

lighting



ACACIA CHANDELIER  
5023

CLASSIC BRONZE PODS WITH GOLD GILDED INTERIOR AND DARK ANTIQUE BRASS FRAME

© 2000-2020 FUSE LIGHTING.  
ALL RIGHTS RESERVED.

**DENNIS MILLER ASSOCIATES**

200 Lexington Avenue Suite 1210 New York, NY 10016  
212.684.0070 Fax.212.684.0776 www.dennismiller.com

# ACACIA CHANDELIER

## 5023

HEIGHT: 3 1/2" (8.9 CM)

DIAMETER: APPROX. 34" (86.4 CM)

CABLES: 56 1/2" (143.5 CM)

OAH: 60" (152.4 CM)  
(CAN BE SHORTENED ON SITE)

CEILING CANOPIES: FOUR 2" (5.1)  
DIA. AND ONE 5" (12.7) DIA. CAN-  
OPIES.

WEIGHT: APPROX. 90 LBS.

WIRING: LED TAPE 2700, 90CRI,  
26.5 WATTS

## METAL FINISHES

BRUSHED BRASS  
LIGHT ANTIQUE BRASS  
DARK ANTIQUE BRASS  
MATTE BRASS  
POLISHED NICKEL  
SATIN NICKEL  
OIL RUBBED BRONZE  
PATINATED STEEL

## POD OPTIONS

CLASSIC BRONZE  
SATIN NICKEL  
INQUIRE FOR CUSTOM POD FINISHES

## DUTCH GILDING

GOLD  
WHITE GOLD  
PLATINUM

## CANOPIES

PRIMER WHITE (PAINTABLE)

## LED (LOW VOLTAGE)

2700K  
90CRI

REMOTE 50WATT LOW-VOLT-  
AGE TRANSFORMER IS REQUIRED  
(SUPPLIED BY FUSE).

LOW VOLTAGE TRANSFORMER  
APPROXIMATE SIZE IS (6.5 X 2.2 X 1.7)

VOLTAGE: 120 VOLTS - WALL TO  
TRANSFORMER

VOLTAGE: 24 VDC - TRANSFORMER TO  
LED TAPE

WIRING: LED TAPE

LED WATTAGE: 4.5 PER FOOT

\*LED TAPE UL LISTED

\*TRANSFORMER ETL LISTED



## INSTALLATION

FOUR 2" CANOPIES MOUNT DIRECTLY  
TO CEILING WITH TOGGLE BOLTS.


A SINGLE 5" CANOPY MOUNTS DI-  
RECTLY TO JUNCTION BOX.

WIRE RUNS ALONG ONE OF THE FOUR  
CABLES INTO THE 5" CANOPY AND  
INTO THE CEILING CONNECTING TO  
THE LOW VOLTAGE TRANSFORMER  
(TO BE PLACED IN AN ACCESSIBLE  
REMOTE LOCATION SUCH AS A CEILING  
RECESS, ATTIC, CLOSET, CABINET OR  
BASEMENT).

INSTALLATION TO BE DONE BY PRO-  
FESSIONAL ELECTRICAL CONTRACTOR  
ONLY.



SCONCE  
**1023**



PENDANT  
**4023**





TABLE LAMP  
**6023**



BOOKSHELF LAMP  
**6023 SL**

fuselighting.com

© COPYRIGHT FUSE LIGHTING.  
ALL RIGHTS RESERVED.

2020